

# Product Environmental Profile



## Display DIRIS Digiware D-70



### The commitments of Socomec to respect the environment

As part of its environmental policy, Socomec is committed to:

- Develop innovating solutions primarily focused on energy efficiency to help its customer in the design of less energy-consuming, better managed and ecofriendly installations.
- Diversify its product offer in the renewable energy and energy efficiency sectors,
- Minimize the environmental impact of its industrial activities through the progressive ISO 14001 certification of its production sites,
- Minimize at the preliminary design stage the environmental impacts of its products taking into account their whole life cycle,
- Provide his customers with reliable data on the environmental performance of the products.

Socomec is member of :

**ecosystem**

Membre de WEEE Europe

**Gimélec**

Environment and sustainable development commissions



## ■ Product information

### Reference product

The representative product is the DIRIS Digiware D-70 with sales reference 48290203.

### Other references covered by this PEP

- DIRIS Digiware D-50 with sales reference 48290204
- DIRIS Digiware D-50 BLE with sales reference 48290206
- DIRIS Digiware D-70 BLE with sales reference 48290207
- ISOM Digiware D-55 Display with sales reference 47290203
- ISOM Digiware D-55h Display with sales reference 47290204
- ISOM Digiware D-75 Display with sales reference 47290205
- ISOM Digiware D-75t Display with sales reference 47290206
- ISOM Digiware D-55 BLE with sales reference 47290210
- ISOM Digiware D-55H BLE with sales reference 47290211
- ISOM Digiware D-75 BLE with sales reference 47290212
- ISOM Digiware D-75H with sales reference 47290213
- ISOM Digiware D-75t BLE sales reference 47290214

### Functional unit

Display electrical measurements of DIRIS Digiware power monitoring modules and communicate over RS485 or Ethernet.

## ■ Material and substances

### Declaration of the constitutive materials according to IEC 62474

Total mass of the reference product (including packaging): 0,269 kg (packaging: 0,082 kg and electronic components: 0,095 kg)

The packaging is composed of: 2 identification stickers, 1 cardboard box, 1 bottom of the crate, 1 cap.

### For the DIRIS Digiware D-70

Metals, 9,8% weight		Plastics, 47,7% weight		Others, 42,5% weight	
Copper and its alloys	5,0%	Others thermoplastics	43,8%	Others Organics	34,3%
Other ferrous alloys – non stainless	1,6%	Other plastics	3,9%	Ceramics and Glass	5,1%
Nickel and its alloys	1,6%			Others Inorganics	3,0%
Other non-ferrous metals and alloys	1,3%				
Precious Metals	0,2%				
Zinc and its alloys	0,1%				
Aluminium and its alloys	0,1%				
Stainless steels	<0,1%				

The estimated content of recycled materials is 43,5%, based on a Life Cycle Analysis model with EIME software.

## Substances management

Socomec is leading a program to limit the use of hazardous substances in the design of new products and to monitor the presence of substances of concern in its supplies to anticipate future use restrictions.



Directive 2011/65/EU : Product references covered by this PEP meet the requirements of the RoHS Directive on the restriction of substances such as lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyl (PBB), polybrominated diphenyl ethers (PBDEs) and phthalates (DIBP, DEHP, BBP, DBP).



To the best of our knowledge, based on the supplier declarations, at the publication date of this document, the product do not contain any other SVHC in a concentration above 0,1% per weight.

## ■ Manufacturing



The products covered by this PEP are manufactured on the production site of Benfeld whose environmental management system has been ISO 14001 certified. Impacts on the environment are reduced by optimizing its energy consumption and by practicing a rigorous waste management

The products covered by this PEP are manufactured on a site where impacts on the environment are reduced by optimizing its energy consumption and by practicing a rigorous waste management.

Moreover, Socomec is committed to the progressive ISO 14001 certification of its manufacturing sites.

## ■ Distribution

As part of its distribution policy aiming to respect the environment, Socomec is in favor of groupage transports and ISO14001 certified logistic partners.  
No reconditioning is needed for this product.



The packaging complies with Directive 94/62/EC.  
The sizing of the packaging has been optimized to ensure the best possible protection of the product at the lowest possible volume in order to reduce the impact of the transport stage on the environment.

Packaging design solutions favors mono-material recyclable cardboard without coloring or bleaching. The wedging of the packaged product is made of recycled cardboard, no polystyrene is used.

## ■ Installation

The installation stage consists in connecting the product to the existing electrical installation. The installation does not generate any significant impacts on the environment, except impacts from packaging waste.

## ■ Use phase

### Consumption scenario

Use phase scenario: European energy mix

Mode	Power consumption of the reference product (W)	Load rate (%)	Time distribution (%)
Active	2,5W	100%	100%

Product power consumption during its total lifespan (10 years): 219 kWh

### Care and maintenance

The product does not require any maintenance under normal conditions of use.

### Consumables

The product does not require consumables

## ■ End of life

### End of life treatment

The following parts require specific care and selective treatment in accordance with Annex VII of the WEEE Directive 2012/19/EU - Waste of electrical and electronic equipment. Maintenance and disassembly should always be conducted by qualified personnel.

Type of component	Item	Part mass	Location
Potential security hazard for operators	LCD display	g	1
Necessity of a selective treatment	LCD display	g	1
	PCBa	g	2



### Recovery potential of the product according to IEC TR 62635

The total potential value of this product is 44,8 %.

This potential value takes into account the material recycling and energy recovery.

## ■ Environmental impacts

### Calculation methodology: life cycle assessment (LCA)



The calculation of the impacts on the environment was made using a life cycle assessment methodology in accordance with the ISO 14040 requirements and with PEP eco passport product category rules. For more details follow the link: [www.pep-ecopassport.org](http://www.pep-ecopassport.org)  
 This study was carried out with the version 5.9.3 of the software EIME with version database CODDE\_2020\_12. The software is distributed by CODDE which is a subsidiary of Bureau Veritas.

The whole life cycle has been taken into account:


Step	Geographical representativeness	Scenario
<b>Manufacturing (M)</b>	Production of electronic components : Asia Production of other components and packaging : Europe Assembly : France	From the raw material extraction to the last Socomec logistic platform, including packaging Waste generated during manufacturing phase are taken into account.
<b>Distribution (D)</b>	Distribution scenario : Europe	From the last Socomec logistic platform to the final customer. No product reconditioning.
<b>Installation (I)</b>	Transport and treatment of packaging wastes : Local	Local road transport of 1000 km of generated wastes to the treatment site, and landfilling
<b>Use phase (U)</b>	Energy mix : Europe	Power consumption required during 15 years and maintenance according to consumption scenario described on page 3.
<b>End Of Life (EOL)</b>	Transport and treatment : Local	Road transport of 1000 km from the final customer to the treatment sites. End of life treatment.

## Environmental impacts of the DIRIS Digiware D-70.

The following impacts have been calculated to best represent geographically and technologically each step of the life cycle.

Indicators	Unit	Total impact	M	D	I	U	EOL
Contribution to global warming	kg CO <sub>2</sub> eq.	1,14E+02	1,18E+01	1,41E-01	1,82E-02	1,02E+02	4,09E-02
Contribution to ozone layer depletion	kg CFC-11 eq.	8,07E-06	1,54E-06	0*	0*	6,53E-06	0*
Contribution to the soil and water acidification	kg SO <sub>2</sub> eq.	4,43E-01	2,25E-02	6,32E-04	7,48E-05	4,19E-01	1,68E-04
Contribution to water eutrophication	kg (PO <sub>4</sub> ) <sup>3-</sup> eq.	3,03E-02	4,32E-03	1,45E-04	5,16E-05	2,57E-02	1,16E-04
Contribution to photochemical ozone formation	kg C <sub>2</sub> H <sub>4</sub> eq.	2,51E-02	1,92E-03	4,49E-05	5,58E-06	2,31E-02	1,26E-05
Contribution to the depletion of abiotic resources - elements	kg Sb eq.	3,28E-03	3,27E-03	0*	0*	8,87E-06	0*
Contribution to the depletion of abiotic resources - fossil fuels	MJ	1,28E+03	1,20E+02	1,98E+00	2,13E-01	1,16E+03	4,78E-01
Contribution to water pollution	m <sup>3</sup>	5,25E+03	9,92E+02	2,31E+01	2,48E+00	4,23E+03	5,57E+00
Contribution to air pollution	m <sup>3</sup>	5,36E+03	9,72E+02	5,76E+00	1,52E+00	4,37E+03	3,41E+00
Use of renewable primary energy (excl. raw materials)	MJ	2,64E+02	4,11E+00	0*	0*	2,60E+02	0*
Use of renewable primary energy used as raw materials	MJ	1,74E+00	1,74E+00	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	2,66E+02	5,85E+00	0*	0*	2,60E+02	0*
Use of non-renewable primary energy (excl. raw materials)	MJ	1,92E+03	1,39E+02	1,99E+00	2,22E-01	1,78E+03	4,99E-01
Use of non-renewable primary energy used as raw materials	MJ	6,01E-01	6,01E-01	0*	0*	0*	0*
Total use of non-renewable primary energy resources	MJ	1,92E+03	1,39E+02	1,99E+00	2,22E-01	1,78E+03	4,99E-01
Use of secondary materials	kg	1,29E-01	1,29E-01	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Use of non-renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Net use of fresh water	m <sup>3</sup>	3,70E+02	5,64E-01	0*	0*	3,70E+02	0*
Hazardous waste disposed of	kg	4,78E+01	4,77E+01	0*	0*	5,36E-02	0*
Non-hazardous waste disposed of	kg	3,87E+02	5,71E+00	0*	9,28E-02	3,81E+02	2,09E-01
Radioactive waste disposed of	kg	2,54E-01	1,92E-03	0*	0*	2,52E-01	0*
Components for reuse	kg	0*	0*	0*	0*	0*	0*
Materials for recycling	kg	0*	0*	0*	0*	0*	0*
Materials for energy recovery	kg	0*	0*	0*	0*	0*	0*
Exported energy	MJ by energy vector	0*	0*	0*	0*	0*	0*
Total use of primary energy during the life cycle	MJ	2,18E+03	1,45E+02	1,99E+00	2,25E-01	2,04E+03	5,06E-01

NB : 0\* means that this impact either represents less than 0.01% of the total life cycle of the reference flow, or has no impact (in the case where the total impact is zero).

Registration number : <b>SOCO-00043-V01.02-EN</b>	Drafting Rules : <b>PCR-ed3-FR-2015 04 02</b>
Verifier accreditation number : <b>VH46</b>	Information and reference documents : <b>www.pep-ecopassport.org</b>
Date of issue : <b>08/2022</b>	Validity period : <b>5 years</b>
<b>Independent verification of the declaration and data, in compliance with ISO 14025 : 2010</b>	
Internal : <input checked="" type="checkbox"/>	External : <input type="checkbox"/>
The PCR review was conducted by a panel of experts chaired by Philippe Osset (SOLINNEN)	
PEP are compliant with XP C08-100-1 : 2016	
The elements of the present PEP cannot be compared with elements from another program	
Document in compliance with ISO 14025 : 2010 « Environmental labels and declarations. Type III environmental declarations »	

*This document is intended to be only informative and non-contractual and does not create any right or obligation or commitment for Socomec towards its associates, customers or any other person or entity. All the values indicated in this document may change depending on many factors (use conditions, applications, installations, environment...). The life time mentioned in this document is only indicative and is not intended to be the minimal, maximal or average life time of the product.*